

MSx SD-WAN Monitoring Guide

Custom Mon Sep 7, 2:08	- Wed Sep 16, 12:58 am < >	,	42369-1	S. J. Bull and	2 7
Custom Plon dep 7, 200					
Traffic Type: Voice					
Vale Claud Enhancements					
Velocloud Enhancements					
MDLC					
MPLS					
Cable					
Sec. 0.0				Windows Update	173.06
. Seb 8. Seb 9. Seb 10.	Sep 11. Sep 12. Sep	13. Sep 14. Sep	15. Sep 16. Sep	Windows Live	151.55
T				HTTP	150.54
Transport Groups	Top Destin	nations by Dor	nain 🔻 🖨	VeloCloud Control	35.37
Public Wired	198.70.247.17			VeloCloud Management	12.63
		_	10 B B B B B B B B B B B B B B B B B B B	Bing	9.35
	121074 50			salesforce	
	13.107.4.50				4.75
	8.254.230.94	1.00	3.4.6.2	speedtest	4.75
	13.107,4.50 8.254,230.94 Ilnw.net	100	33 16 1	Speedtest Google Ads	4.75 2.69 2.22
	13.107.4.50 8.254.230.94 Ilnw.net		22 6.	Google Ads Google	4.75 2.69 2.22
	13.107.4.50 8.254.230.94 Ilnw.net	12/14/2	1	Speedtest Google Ads Google	4.75 2.69 2.22 2.15
	13.107.4.50 8.254.230.94 Ilnw.net	1		Speedtest Google Ads Google	4.75 2.69 2.22 2.15





The MSx SD-WAN service includes powerful reporting capabilities which are accessible via the Orchestrator. The Orchestrator provides deep insight into how your WAN service is performing and provides business intelligence on your usage. You can view the top applications (i.e. Office 365, web browsing, Salesforce, AWS, etc.) that are consuming your bandwidth as well as who

your top users are within your environment.

The TPx team will provide you with the URL and credentials to access the portal, if you did not receive a login, please contact your Project Manager or Project Engineer.

Two-factor authentication is enabled

in this screen.

Welcome To TPX Net	work Orchestrator	
Username:	UserName@tpx.com	Forgot your password?
Password:	•••••	for assistance.
	Sign In	
Welcome To		
TPX Net	work Orchestrator	
Please contai	e check your mobile phone for an SMS ning your six digit authorization pin.	No SMS message? Contact support@tpx.com for assistance.
Pin:		
	Cancel	

Network Overview

The Network Overview feature helps to monitor networks by checking the Edge and Link (activated Edge) status summary. Clicking **Monitor > Network Overview** in the navigation panel opens the Network Overview screen, which provides a visual summary about the enterprises running SD-WAN Edge devices, Non VMware SD-WAN Sites, profiles, segments, software versions, and their system configuration time and run time statuses. **Green=Connected; Amber=Degraded; Red=Down.**

5-site					Recently Viewed	Superuser Op	erator Help	super@velocloud.net
Monitor	Network Ove	rview			Re	fresh Interval: •	pause 🔍 30a	• 60s • 5min
 Edges Network Services Routing 		Edge	es			Li	inks	
Alerts Events Configure	5 out of 5 activated	1 Down	0 Degraded	4 Connected	9	1 Down	0 Unstable	8 Stable
Test & Troubleshoot	0 Hubs	0	0	0	0 Hub Links	0	0	0
Aunmistration	Edge	Statu	is HA	Links	Cluster Name	e	Activated	
	b5-edge1		•	0=0 2	none			Fri Jul 28, 17:35:07
	b4-edge1		•	↔ 2	none			Fri Jul 26, 17:35:06
	b3-edge1		•	0+0 2	none			Fri Jul 26, 17:35:05
	b2-edge1		•	<i>9</i> 6 1	<→ 2 none			Fri Jul 26, 17:35:04
	b1-edge1		•		none			
								•
								View Al
	O Edges with enabled	0 Error	0 Off	0 On	0 Edges with enabled	0 Failed	0 Pending	0 Ready
	VNF				VeloCloud Active Star	ndby Pair		
	0 out of 0 enabled	0 Conne	cted	<mark>0</mark> Offline	3 out of 3 used	out	3 t of 3 ivated	3 out of 5 up to date
	Non-VeloCloud Si	tes			Profiles	Seg	ments	Software Version



The **Network Overview** screen (previous page) presents the overall summary information about a network in dashboard sections. These statistics include the following information about the Edges and Links:

- Total number of Edges
- Total number of Edge Hubs
- Total number of Links
- Total number of Hub Links
- Count of Edges/Edge Hubs (Connected, Degraded, and Down)
- Count of Link/Hub Links (Stable, Unstable, and Down)

Edges

You can monitor the status of Edges and view the details of each Edge like the WAN links, top applications used by the Edges, usage data through the network sources and traffic destinations, business priority of network traffic, system information, and details of Gateways connected to the Edge. To monitor the Edge details:

- In the Enterprise portal, click **Monitor > Edges**.
- The Edges page displays the Edges associated with the enterprise.



The page displays the following details of Edges:

- **Table of Edges** Lists all Edges provisioned in the network.
- Search Enter a term to search for s specific detail. Click the drop-down arrow to filter the view by specific criteria.
- **Columns** Click to show or hide the columns. By default, Edge and Status information are displayed.
- **Reset** Click to reset the view to default settings.
- Refresh Click to refresh the details displayed with the most current data.
- **Export** Click to export all data to a file, in CSV format.

Click the link to an Edge to view the details pertaining to the selected Edge. Click the relevant tabs to view the corresponding information. Each tab displays a drop-down list at the top which allows you to select a specific time period. The tab displays the details for the selected duration. For each Edge, you can view the following details:

- Overview Tab
- Sources Tab
- QoE Tab
- Destinations TabBusiness Priority Tab
- Applications Tab

Transport Tab

System Tab



Edges > Overview

The **Overview** tab of an Edge in the monitoring dashboard displays the details of WAN links along with bandwidth consumption and network usage. To view the information of an Edge:

- In the Enterprise portal, click Monitor > Edges.
- Click the link to an Edge and the **Overview** tab is displayed by default.

The Overview tab displays the details of links with status and the bandwidth consumption.

Monitor	Monitor Edge>	10	n <u>—</u>							?
Network Overview	bl-edgel		d) 🔽							
📥 Edges				_						
Network Services	Overview QoE	Transport	Applications Sources	Destinations	Business Priority	System				
Routing	Past 12 Hours	 Wed Sep 2, 	10:13 - now	< >						
Alerts										
Events	Lat Link Otatur									
Reports	LINK Status	updated a few sec	onds ago					Stay	in live mod	le 😈
Configure	Links	Link Status	Interface (WAN Type)	Т	Throughput Bandwid	lth	Pre-Notifications 🚯	Alerts 🚯	Signal	Θ
Test & Troubleshoot	169.254.6.34 (1) 169.254.6.34	6-0	GE4 (Ethernet)		54.40 kbps 167.71 M	Apps Apps	🗹 Edit	🗹 Edit	N/A	
Administration	169.254.7.10 (1) 169.254.7.10		GE3 (Ethernet)		6.27 kbps 170.17 M 5.87 kbps 175.16 M	Лъра Лъра	🗹 Edit	🗹 Edit	N/A	
Configure this Edge										
Events from this Edge										
Remote Actions	Lul Bandwidth	Usage wed Se	p 02, 10:13 - 22:28 , Total: 11	9.70 MB						
😑 Generate Diagnostic Bundle	Top Applications			Ð	Top Ca	tegories			0	Ð
Remote Diagnostics	Name			Volume						_
	SD-WAN Control			113.05 MB			SD-WAN			
	SD-WAN Management			0.05 MB			Network Service			
	Top Operating Syst	ems		Ð	Top So	urces			(Ð
	200M					200M -				
						100M				
	100M					20011				
						ом —				
	ом —		4 ³⁶⁸				50Man C.			
						To	tal devices: 1. Average use per devic	e: 119.70 MB.		

You can choose to view the Edge information live by selecting the **Stay in live mode** checkbox in the upper right. When this mode is enabled, live monitoring of the Edge happens and the data in the page is updated whenever there is a change. Live mode is automatically moved to offline mode after a period of time to reduce the network load.

The Links Status section displays the details of Links, Link Status, WAN Interface, Throughput, Bandwidth and Signal.

The **Top Consumers** section displays graphical representation of bandwidth and network usage of the following: Applications, Categories, Operating Systems, Sources, and Destinations of the Edges. Click **View Details** in each panel to navigate to the corresponding tab and view more details.

Hover the mouse on the graphs to view more details.



Edges > QoE

The VMware SD-WAN Quality of Experience (QoE) tab shows the VeloCloud Quality Score (VQS) for different applications. The VQS rates an application's quality of experience that a network can deliver for a period of time.

Click the **Monitor > Edges > QoE** tab to view the following details:

- In the Enterprise portal, click Monitor > Edges.
- Click the link to an Edge and the **Overview** tab is displayed by default.



Traffic Type

There are three different traffic types that you can monitor (Voice, Video, and Transactional) in the QoE tab. You can hover over a WAN network link, or the aggregate link to display a summary of Latency, Jitter, and Packet Loss.

VeloCloud Quality Score

The VeloCloud Quality Score (VQS) rates an application's quality of experience that a network can deliver for a given time frame. Some examples of applications are: video, voice, and transactional. QoE rating options are shown in the table below:

Rating Color	Rating Option	Definition
Green	Good	All metrics are better than the objective thresholds. Application SLA met/exceeded.
Yellow	Fair	Some or all metrics are between the objective and maximum values. Application SLA is partially met.
Red	Poor	Some or all metrics have reached or exceeded the maximum value. Application SLA is not met.

QoE Examples

The following images (next page) show examples of QoE with before and after voice traffic scenario problems and how VMware SD-WAN solved them. The red numbers in the following images represent the scenario numbers in the associated table.



QoE Examples

Scenario	Issue	VMware SD-WAN Solution
1	MPLS is down	Link steering
2	Packet loss	Forward error correction
3	MPLS is down; Jitter on Comcast	Link steering and jitter buffering

1 & 2: Link Steering and Forward Error Correction





3: : Link Steering and Jitter Buffering

Edges > Transport

You can monitor the WAN links connected to a specific Edge along with the status, interface details, and other metrics. At any point of time, you can view which Link or Transport Group is used for the traffic and how much data is sent in the **Monitor > Edges > Transport** tab. When you click the Transport tab, the Links screen is displayed by default. The screen displays Sent and Received data for your links.

Monitor	Monitor Edge >							?
Network Overview	bl-edgel (Connect)	ed) 🔽						
📥 Edges	Overview OoF Trenenet	Applications	Destinations	Rusiness Drissity	Custom			
Network Services	Overview QOE Transport	Applications Sources	Destinations	Business Priority	System			
Routing	Past 12 Hours 🔹 Thu Sep 3	3, 3:38 - now	< >					
Alerts								
Events	Bytes Received/Sent 💙			Show TCP/U	DP Details	Stop Live Monitoring	Transport G	Froups Links
Reports								
Configure	169.254.6.34 (169.254.6.34)			69.25	4.7.10 (169.)	254.7.10)		
Test & Troubleshoot			10.00 kB					10.00 kB
Administration			Rec					Rec
Configure this Edge			5.00 kB 😫					5.00 kB ⊈ ⊈
Events from this Edge								0
Remote Actions	15:36 15:37 15:38	15:39 15:40	0	15:36	15:37	15:38 15:39	15:40	0
😌 Generate Diagnostic Bundle			10.00 kB					10.00 kB
Remote Diagnostics			1					
			5.00 kB					5.00 kB
			0				-	0
	15:36 15:37 15:38	15:39 15:40		15:36	15:37	15:38 15:39	15:40	
				DP 🔽 ICMP	🗹 other			



×



The links associated with an Edge are displayed in at the bottom of the screen under the Link column, along with the status for Cloud and VPN, WAN Interface, Application details, and details of Bytes. Hover the mouse on the graphs to view more details.

Transport Groups by Total Bytes

By default the **Scale Y-axis evenly** checkbox is enabled. This option synchronizes the Y-axis between the charts. If required, you can disable this option.

Choose the metrics from the drop-down to view the details related to the selected parameter. The bottom panel displays the details of the selected metrics for the links or the transport groups. Click the arrow prior to the link name or the transport group to view the break-up details. To view drill-down reports with more details, click the links displayed in the metrics column.

The image on the right shows a detailed report of transport groups with top applications:

Thu Sep 03, 03:38 – 15:46 Public Wired Public Wired 213.17 MB Close

Edges > Applications

You can monitor the network usage of applications or application categories used by a specific Edge.

Click the **Monitor > Edges > Applications** tab. At the top of the page, you can choose a specific time period to view the details of applications used for the selected duration. Click **Categories** to view similar applications grouped into categories. Hover the mouse on the graphs to view more details.





Choose the metrics from the drop-down to view the details related to the selected parameter. By default the **Scale Y-axis evenly** checkbox is enabled. This option synchronizes the Y-axis between the charts. If required, you can disable this option.

The bottom panel displays the details of the selected metrics for the applications or categories. To view drill-down reports with more details, click the links displayed in the metrics column. The following image on the right shows a detailed report of top applications.



Edges > Sources

You can monitor the network usage of devices and operating systems for a specific Edge. Click **Monitor > Edges > Sources.**



At the top of the page, you can choose a specific time period to view the details of clients used for the selected duration. Click **Operating Systems** to view the report based on the Operating Systems used in the devices. Choose the metrics from the drop-down to view the details related to the selected parameter. By default the **Scale Y-axis evenly** checkbox is enabled. This option synchronizes the Y-axis between the charts. If required, you can disable this option. Hover the mouse on the graphs to view more details.

The bottom panel displays the details of the selected metrics for the devices or operating systems. To view drill-down reports with more details, click the links displayed in the metrics column. The right image shows a detailed report of top clients.



Click the arrows displayed next to **Top Applications** to navigate to the Applications tab.



Destinations

You can monitor the network usage data of the destinations of the network traffic. Click the **Monitor > Edges > Destinations** tab to view the following:



At the top of the page, you can choose a specific time period to view the details of destinations used for the selected duration. You can view the report of Destinations by Domain, FQDN, or IP address. Click the relevant type to view the corresponding information. Hover the mouse on the graphs to view more details.

Choose the metrics from the drop-down to view the details related to the selected parameter. By default the **Scale Y-axis evenly** checkbox is enabled. This option synchronizes the Y-axis between the charts. If required, you can disable this option.

The bottom panel displays the details of the selected metrics for the destinations by the selected type. To view drill-down reports with more details, click the links displayed in the metrics column. The right image shows a detailed report of top domains.

Click the arrows displayed next to **Top Applications** to navigate to the Applications tab.





Business Priority

You can monitor the Business policy characteristics according to the priority and the associated network usage data for a specific Edge. Click the **Monitor > Edges > Business Priority** tab to view the following:



At the top of the page, you can choose a specific time period to view the details of the priorities for the selected duration. Choose the metrics from the drop-down to view the details related to the selected parameter.

By default the Scale Y-axis evenly checkbox is enabled. This option synchronizes the Y-axis between the charts. If required, you can disable this option. Hover the mouse on the graphs to view more details. The bottom panel displays the details of the selected metrics for the business priorities.

System

You can view the detailed network usage by the system for a specific Edge. To view the details of system information:

- In the Enterprise portal, click Monitor > Edges.
- Click the link to an Edge and the **System** tab.

The **System** tab (next page) displays the details of network usage by the system for the selected Edge. The page displays graphical representation of usage details of the following over the period of selected time duration, along with the minimum, maximum, and average values.

- CPU Percentage Percentage of usage of CPU
- Memory Usage Percentage of usage of memory
- Flow Counts Count of traffic flow
- Handoff Queue Drops Count of packets dropped due to queued handoff
- **Tunnel Count** Count of tunnel sessions

Hover the mouse on the graphs to view more details.





Alerts

SD-WAN Orchestrator provides an alert function to notify one or more Enterprise Administrators (or other support users) when a problem occurs. You can access this functionality by clicking **Alerts** under Monitor in the navigation panel.

You can send Alerts when a SD-WAN Edge goes offline or comes back online, a WAN link goes down, a VPN tunnel goes down, or when an Edge HA failover occurs. A delay for sending the alert after it is detected can be entered for each of the alert types. You can configure alerts in **Configure > Alerts and Notifications**.

Note: If you are logged in using a user ID that has Customer Support privileges, you will only be able to view SD-WAN Orchestrator objects. You will not be able to create new objects or configure/update existing ones.

Monitor	Alerts			
🛎 Edges				
Metwork Services	Past 12 Months	Feb 9, 2015 13:4	3 now K Filter	
📥 Alerts				
Events				
Firewall Logs			Items 1 — 10 of 10.	Show 30 🔻 per page.
Configure				
Test & Troubleshoot	Time	Туре	Description	Status 🔺
Test & Houbleshoot	Tue Jul 21 2015, 14:16	Edge Down	Edge VeloAcme VPN Edge	Closed
Administration	Tue Jul 14 2015, 13:02	Edge Down	Edge VeloAcme VPN Edge	Closed
	Tue Jul 07 2015, 10:51	Link Down	AT&T U-verse (INTERNET1) Link down on Edge VeloAcme VPN Edge	Closed
	Mon Jul 06 2015, 16:04	Edge Down	Edge VeloAcme VPN Edge	Closed
	Mon Jul 06 2015, 11:02	Edge Down	Edge VeloAcme Internet Edge	Closed
	Mon Jul 06 2015, 08:47	Edge Up	Edge VeloAcme Internet Edge	Closed
	Mon Jul 06 2015, 08:13	Edge Down	Edge VeloAcme Internet Edge	Closed
	Fri Jul 03 2015, 17:10	Edge Down	Edge VeloAcme Internet Edge	Closed
	Thu Jul 02 2015, 16:10	Edge Up	Edge VeloAcme Internet Edge	Closed
	Thu Jul 02 2015, 15:01	Edge Down	Edge VeloAcme Internet Edge	Closed



Events

The Events page in the navigation panel displays the events generated by the SD-WAN Orchestrator. These events can help you determine the operational status of the VMware SD-WAN system. You can click the link to an Event link displayed in the Events page to view more details.

Monitor	Alerts			5				
 Luges Network Services 	Past 12 Months 💌	Past 12 Months Feb 9, 2015 13:43 now Filter						
Alerts								
Events								
Firewall Logs			Items 1 — 10 of 10.	Show 30 🔻 per page.				
Configure								
Test & Troubleshoot	Time	Туре	Description	Status 🔺				
Test & Houbleshoot	Tue Jul 21 2015, 14:16	Edge Down	Edge VeloAcme VPN Edge	Closed				
Administration	Tue Jul 14 2015, 13:02	Edge Down	Edge VeloAcme VPN Edge	Closed				
	Tue Jul 07 2015, 10:51	Link Down	AT&T U-verse (INTERNET1) Link down on Edge VeloAcme VPN Edge	Closed				
	Mon Jul 06 2015, 16:04	Edge Down	Edge VeloAcme VPN Edge	Closed				
	Mon Jul 06 2015, 11:02	Edge Down	Edge VeloAcme Internet Edge	Closed				
	Mon Jul 06 2015, 08:47	Edge Up	Edge VeloAcme Internet Edge	Closed				
	Mon Jul 06 2015, 08:13	Edge Down	Edge VeloAcme Internet Edge	Closed				
	Fri Jul 03 2015, 17:10	Edge Down	Edge VeloAcme Internet Edge	Closed				
	Thu Jul 02 2015, 16:10	Edge Up	Edge VeloAcme Internet Edge	Closed				
	Thu Jul 02 2015, 15:01	Edge Down	Edge VeloAcme Internet Edge	Closed				

The Events feature is useful for obtaining the following information:

- Audit trail of user activity [filter by user]
- Historical record of activity at a given site [filter by site]
- Record of outages and significant network events [filter by event]
- Analysis of degraded ISP performance [filter by time period]
- Auto Rollback to the Last Known Good Configuration

If an Administrator changes device configurations that cause the Edge to disconnect from the Orchestrator, the Administrator will get an Edge Down alert. Once the Edge detects that it cannot reach the SD-WAN Orchestrator, it will rollback to the last known configuration and generate an event on the Orchestrator titled, "bad configuration."

For additional information, please reach out to TPx Communication's hotline at 877-487-8722.